

Technical field of the invention

Background of the invention

The data transfer architectures are divided into two main categories, i.e., a non-access stratum and an access stratum. The non-access stratum offers higher layer (e.g., a network layer) signaling, such as Mobility Management (MM) and Call Control (CC), between network elements. The access stratum is the functional grouping consisting of the parts in the infrastructure and in the user equipment and the protocols between these parts being specific to the access technique. The access stratum provides services related to the transmission of data over the radio interface and the management of the radio interface to the

5
10

20
25
30
35

5

10

15

25

35

needed. Common transport channels are shared by several users, and inband identification of UE is needed. The identification of a UE is achieved by a Radio Network Temporary Identity (RNTI) field of MAC-layer. The
5 multiplexing of the transport channels onto the same or different physical channels is carried out by layer 1.

The channel coding and multiplexing generally comprise the following steps (not necessarily in this order):

- 10 CRC (Cyclic Redundancy Code) attachment is added to a transport block.
Inserting a tail bit attachment to the 'transport block + CRC'.
Convolutional coding (or alternatively turbo coding
15 or alternatively no coding) of 'transport block + CRC + tail bit attachment'.
Rate matching.
1st interleaving.
Radio frame segmentation.
20 (Possible) 2nd interleaving.
Transmitting radio frames through the physical channel to the receiving party (i.e., UE or Access Network or Core Network).
- 25 The present day decoding and demultiplexing methods are based on the technical specifications of 3GPP. The following steps apply to common channel processing. After receiving the radio frame in a receiver (e.g., a RAKE-receiver of a UE), the radio frame is processed by the UE.
30 The processing includes deinterleaving, rate matching, turbo decoding (or alternatively convolutional decoding or alternatively no decoding), calculating a CRC checksum. Then the result of the previous processes will be transferred to the MAC, which identifies (if needed) the
35 UE by identifying a Radio Network Temporary Identity (RNTI) transmitted in a radio frame. In other words, a UE decodes all packets on all transport channels multiplexed

00260-89655660

5

10

15

20

30

35

100-443886-100

equipment (UE) connected to a communications network, the method comprising:

receiving radio frames in a receiver of the user equipment;

5 identifying a Transport Format Combination Indicator (TFCI) of the radio frame in the user equipment; and

determining whether the received radio frame includes transport blocks that are not directed to the user equipment.

10

According to the first aspect of the present invention, the determining preferably comprises:

identifying which transport channels include transport blocks in the received radio frame;

15 determining which of these transport channels carry transport blocks that are not directed to the user equipment; and

determining that these transport channels are not directed to the user equipment.

20

According to a second aspect of the present invention there is provided a method of processing received data at a user equipment (UE) connected to a communications network, the method comprising:

25 receiving radio frames in a receiver of the user equipment;

identifying transport block sizes of the radio frame in the user equipment; and

30 determining whether the received radio frame includes transport blocks that are not directed to the user equipment.

According to the second aspect of the present invention, the determining preferably comprises:

35 comparing the received transport block sizes to the transport block sizes used by the radio access bearer services of the user equipment;

09955968-092001

determining that these transport blocks are not
5 directed to the user equipment.

Preferably, in case the received transport blocks may be directed to the user equipment, the user equipment further processing the received transport blocks. More preferably the transport blocks processing comprises one or multiple of the following processes: deinterleaving, rate matching, error control decoding, calculating a cyclic redundancy code (CRC) checksum, processing the data in a medium access control (MAC)-layer.

25 The method achieves an earlier recognition of the destination of the transport blocks (i.e., recognizing if the transport blocks are not directed to the user equipment), which provides fewer functions to be processed by the UE, because the UE can earlier determine whether
30 the transport blocks may be destined to the UE, in which case they will be further processed, or to some other UE. This will also lead to power savings, because the transport blocks that are not destined to the UE(s) need not be processed any further, and thus they can be
35 discarded at an earlier stage.

According to a third aspect of the present invention there is provided a user equipment comprising:

- means for receiving radio frames;
- means for identifying a Transport Format Combination Indicator (TFCI) of the radio frame; and
- means for determining whether the received radio frame includes transport blocks that are not directed to the user equipment.

According to a fourth aspect of the present invention there is provided a user equipment comprising:

- means for receiving radio frames;
- means for identifying transport block sizes of the radio frame in the user equipment; and
- means for determining whether the received radio frame includes transport blocks that are not directed to the user equipment.

Preferably, the user equipment further comprises processing means for further processing the transport blocks. More preferably, the processing means is capable of processing at least one of the following processes: deinterleaving, error control decoding, calculating cyclic redundancy code (CRC) checksum, processing a data in a medium access control (MAC)-layer.

Preferably, the means for receiving radio frames is a RAKE-receiver.

Brief description of the drawings

For a better understanding of the present invention and in order to show how the same may be carried into effect reference will now be made, by way of example, to the accompanying drawings, in which:

Figure 1 shows schematically a user plane in a UMTS, in which the present invention can be implemented.

0055968-092001

Figure 3 shows schematically model of the UE's physical layer for a downlink according to one embodiment of the present invention.

Figure 5 is a flowchart illustrating the method of another embodiment of the present invention.

Detailed description of certain embodiments

30 Figure 2 shows a Radio Interface protocol architecture
around a physical layer 201 (Layer 1). The physical layer
201 interfaces a Medium Access Control (MAC)-layer 202,
which is a sub-layer of Layer 2, and the Radio Resource
Control (RRC)-layer 203 of Layer 3. The physical layer 201
35 offers different transport channels 204 to MAC 202. MAC
202, in turn, offers logical channels 205 to the Radio
Link Controller (not shown in figure 2), which is a sub-

5

10

25

30

35

After a data stream of the CCTrCH is received from the physical channel, the data stream of the CCTrCH is fed to a data decoding and demultiplexing unit that decodes and demultiplexes the CCTrCH's data stream onto transport channels (i.e. one PCH and two FACHs in figure 3). Even though, there is shown one PCH and two FACHs in figure 3, the skilled person in the art appreciates that three transport channels is just an example used to illustrate layer 1 demultiplexing and alternative channel combinations may be applied to the present invention. There may be e.g., three FACHs and no PCH. In the simplest form there is only one FACH in question.

Referring now to figure 4, which illustrates the inventive concept of the present invention. After receiving the data in a physical entity of UE (e.g., by a RAKE-receiver) (step 401), the physical layer control information is decoded from the radio frame (step 402). On step 403, the user equipment identifies a TFCI (Transport Format Combination Indicator). Thereafter, on step 404, the UE determines whether the received transport blocks of the radio frame are not directed to the user equipment (or may be directed to the user equipment). If the transport blocks of the radio frame may not be directed to the UE but to some other UE (not shown in the figure), the UE ends processing of these transport blocks (step 405). In case the received transport blocks of the radio frame may be directed to the UE, the UE further processes the transport blocks as following. The UE does deinterleaving (step 406), the rate matching (step 407), error control decoding (e.g., Viterbi or turbo) (step 408), calculates the CRC checksum (step 409), and transfers the received transport blocks to a MAC-layer for further processing (step 410).

35

The present invention covers two embodiments to determine (in step 404 in figure 4) whether the radio frames are not

T00260-8965560

directed to the user equipment or may be directed to the user equipment.

The preferred embodiment of the present invention can be implemented when several FACHs are multiplexed onto the same physical channel. Since a transport channel can only support a constant transmission quality (e.g., block error rate) target, and a limited set of transport block sizes several FACHs are needed to support Radio Access Bearers (RABs) with different requirements on transmission quality. At RAB establishment, a network informs the user equipment on which FACH the information will be transmitted. Upon receiving a CCTrCH frame, the user equipment can by reading the TFCI determine which are FACHs that include data in this frame. If no data is received on the FACH, onto which the RAB(s), which the user equipment has established, is present in the CCTrCH frame, the user equipment can stop processing this frame.

As for illustrating the preferred embodiment of the present invention, let's consider the following simplified situation. A UMTS Terrestrial Radio Access Network (UTRAN) is configured to support two basic services: Radio Access Bearer 1 (RAB1) for best effort WWW IP traffic and Radio Access Bearer 2 (RAB2) for Highway traffic information service. Because of the different quality requirements of the services, they are mapped onto different FACHs. Both FACHs are mapped onto the same Downlink Physical Data Channel (DPDCH) on layer 1. However, the bandwidth allocated on FACH for RAB1 is much larger than for RAB2, because of the traffic characteristics and requirements. A UE not implementing the present invention would have to decode all information on the DPDCH up to MAC level to read the RNTI and determine whether the information was addressed to it or not. A UE implementing the present invention can already after reading the TFCI cease to process the information on transport channels carrying the

T00260-8965660

services it does not use. E.g., for UEs only using RAB2, this is a considerable gain, since the FACH carrying RAB1 has a higher bit rate, and therefore, it requires more processing to decode.

5

Referring now to figure 5, which illustrates another embodiment of the inventive concept of the present invention. After receiving the data in a physical entity of UE (e.g., by a RAKE-receiver) (step 501), the physical layer control information is decoded from the radio frame (step 502). On step 503, the user equipment identifies the transport block sizes of the radio frame in the user equipment. Thereafter, on step 504, the UE determines whether the received transport blocks are of the size that the transport blocks may be directed to the user equipment (or may be directed to some other user equipment). If the transport blocks were not of the size that may be directed to the UE, the UE ends processing of the transport blocks (step 505). In case at least one of the received transport blocks are of the size that may be directed to the UE, the UE further processes the radio frame as following. The UE does deinterleaving (step 506), the rate matching (step 507), error control decoding (e.g., turbo or Viterbi) (step 508), calculates the CRC checksum (step 509), and transfers the received transport blocks to a MAC-layer for further processing (step 510). It should be noted that only the transport blocks of the size that may be directed to the UE need to be processed beyond step 506.

Another embodiment of the present invention also uses the block size to determine whether the CCTrCH frame needs further processing or not (i.e., are the transport blocks not directed to the user equipment). As disclosed in the preferred embodiment of the present invention, one FACH can only support a limited set of block sizes. At RAB establishment, the user equipment is informed of the transport block (TB) sizes used for each RAB. By using

T00260-8965660

this information, the user equipment can quit processing transport blocks that are of other sizes, since they belong to services the user equipment has not subscribed to.

5

Even though the present invention discloses a preferred embodiment and another embodiment, both embodiments may be used simultaneously.

10 Figure 6 shows a possible frame structure for a common control physical channel that is used to carry FACH and/or PCH. A frame includes multiple slots, which in turn, comprise a Transport Format Combination Indicator (TFCI) field, a data field and a pilot field.

15

The Transport Format Combination Indicator is a presentation of the current Transport Format Combination (TFC), which is a combination of the currently valid Transport Formats that can be submitted simultaneously to the layer 1 for transmission on a Coded Composite Transport Channel of a user equipment. TFCI is used to inform the user equipment of the currently valid Transport Format Combination and hence how to decode, demultiplex and deliver the received data on the appropriate transport channels.

25

The data field contains data bits that are transported to the user equipment.

30 The pilot field includes the pilot symbols used for channel estimation.

It will be appreciated by the skilled person that various modifications may be made to the above described embodiments without departing from the scope of the present invention. For example, there may be several FACHs

35

T00260-89655660

and no PCH encoded and multiplexed on together forming a CCTrCH.

0995968-092001